



# counterloop

audio frequency  
induction loop systems

## Cost effective and stylish

### Counter Top Unit

Counter Loop is a mains powered induction loop amplifier that provides a cost effective and stylish solution for counter top applications or small rooms up to 25m<sup>2</sup>.

The unit has two microphone inputs as standard allowing the freedom to have two separate sound sources fed in to the amplifier.

The Counter Loop is installed with its own power supply, external loop and microphone.

### 'Fit and Forget'

Once installation is complete, Counter Loop is literally a 'Fit & Forget' solution. It should be left on 24/7.

All units feature the distinctive logo, which makes them instantly recognisable.

### Power & Active LED's




The top face of the amplifier houses two brightly coloured LEDs. The 'Power' LED illuminates when power to the unit is applied, whilst the 'Active' LED will flicker during use to denote that speech is being received and transmitted inductively from the loop.

### Optional Features (special order)

#### Optional 'Gooseneck' Microphone

Particularly useful at busy and noisy reception and counter areas, a 'Noise Cancelling' Gooseneck Microphone is available.

#### Additional Electret Microphone



# Counter Loop Specifications

## Set-up & Operation

The unit comes pre-set from the factory, so no user adjustments are necessary. Commissioning to take place with a calibrated field strength meter.

## Power Supply

Only the APPROVED POWER ADAPTOR SUPPLIED MUST BE USED. The amplifier is designed to remain switched on permanently or can be switched off overnight depending on user preference.

Overall dimensions:	185mm x 87mm x 45mm
Weight:	220g
Finish:	ABS, fine textured
Fixing holes:	For 2 off No.8 screws on a 140mm pitch
Audio inputs:	2 off 3.5mm jack sockets with phantom power for unbalanced electret microphones
Microphone sensitivity:	-62dB $\pm$ 3dB (0dB = 1V/ $\mu$ Bar @ 1KHz)
Output:	2 way screw-less terminal block for loop connection
Output current:	0.7 A <sub>RMS</sub> (@ 1KHz) 2.8 A <sub>PEAK</sub> (125ms)
Loop impedance:	0.1 to 1 ohm @ 1KHz
Dynamic range:	> 60dB
THD+N (amplifier):	< 0.5%
DC input:	15V @ 1A maximum
Power supply:	Input: 100 – 240V <sub>AC</sub> 50 / 60Hz @ 0.45A maximum Output: 15V <sub>DC</sub> @ 1A maximum Short circuit protected
Approvals:	EN50081-1: 1992 EN61000-3-2: 2000 EN61000-3-3: 1995, A1: 2000 EN61000-6-1: 2001 EN60950: 2000

## Safety

Counter Loop and its associated power supply are designed for indoor use only. They contain no user-serviceable parts. **DO NOT REMOVE THE OUTER COVERS.**

The product herewith complies with the requirements of Directives 89/336/EEC; 1995/5/EC and 73/23/EEC; 1995/5/EC and carries the CE-marking accordingly.

Fully compliant to EN60118-4.

All information contained in this specification is believed to be correct at the time of printing. All aspects of this specification are subject to change without prior notice. All rights are reserved.

### Vivid Acoustic Systems Limited

DTS Building, Nelson Way  
Cramlington  
Northumberland NE23 1WG  
Tel: 01670 710740 Fax: 01670 710750  
enquiries@vivid-acoustics.com



audio frequency  
induction loop systems

All aspects of this specification are subject to change without prior notice. All rights are reserved.